

# 3 Ft. 16W (25/30W Replacement) Daylight Deluxe (6500K) G13 Base Direct Replacement (Type A) (T8 & T12 Replacement) LED Linear Tube

## Features

- Works with most magnetic and electronic ballasts, no rewiring is required
- Shatter-resistant and mercury-free, no special disposal is required
- Flicker-free, instant ON illumination at full brightness



## Specifications

<b>Item Number</b>	<b>Bulb Shape</b>	<b>Bulb Type</b>	<b>Bulb Base</b>
T36/865/LEDG2	T8	Tubular	G13
<b>Tube Type</b>	<b>Technology</b>	<b>Brightness (LUMENS)</b>	<b>Lumen Efficiency (LPW)</b>
Type A	LED - SMD	1450	90.63
<b>Color Accuracy (CRI)</b>	<b>Color Temperature (CCT)</b>	<b>Life Hours</b>	<b>Life Years</b>
80	6500	50000	45.7
<b>Replacement</b>	<b>Annual Energy Cost</b>	<b>Energy Efficiency</b>	<b>Energy Used (Wattage)</b>
25 30	1.93	36.0%	16
<b>Battery Operated</b>	<b>Pack Quantity</b>	<b>Smart</b>	<b>Portable</b>
NO	1	No	NO
<b>Dimmable</b>	<b>Hardwire</b>	<b>Safety Location</b>	<b>Energy Star</b>
NO	NO	Damp	No
<b>CEC Compliant</b>	Not Regulated		