

# 4 Ft. 36W (54W Replacement) Daylight (5000K ) Bi-Pin Base T8 High Output Ballast Bypass (Type B) Linear LED (2-Pack)

## Features

- Converts conventional fluorescent lighting to energy saving LED technology
- Requires re-wiring to bypass or remove the ballast, enabling the most efficient operation and less maintenance over time
- Energizing crisp Daylight color illuminates fine details with invigorating cool light



## Specifications

<b>Item Number</b>	<b>Item Length (In)</b>	<b>Item Width (In)</b>	<b>Bulb Shape</b>
T848HO/850/B/LED/2	47.6	1.1	T8
<b>Bulb Type</b>	<b>Bulb Base</b>	<b>Bulb Finish</b>	<b>Tube Type</b>
Tubular	Bi-Pin	Frost	Type B
<b>Technology</b>	<b>Brightness (LUMENS)</b>	<b>Lumen Efficiency (LPW)</b>	<b>Color Accuracy (CRI)</b>
LED - SMD	4000	111.11	80
<b>Color Temperature (CCT)</b>	<b>Life Hours</b>	<b>Life Years</b>	<b>Voltage</b>
5000	25000	22.8	120-277
<b>Replacement</b>	<b>Annual Energy Cost</b>	<b>Energy Efficiency</b>	<b>Energy Used (Wattage)</b>
54	4.34	33.3%	36
<b>Battery Operated</b>	<b>Pack Quantity</b>	<b>Smart</b>	<b>Portable</b>
NO	2	No	NO
<b>Dimmable</b>	<b>Hardwire</b>	<b>Enclosed Fixture Rated</b>	<b>Safety Location</b>
NO	NO	YES	Damp
<b>Energy Star</b>	<b>CEC Compliant</b>	<b>Warranty Years</b>	
No	Not Regulated	5	