

8 Ft. 40W (59W Replacement) Daylight (5000K) FA8 Base (T8 And T12 Replacement) Ballast Bypass (Type B) LED Linear Tube (2-Pack)

Features

- Ballast bypass installation requires direct wiring for longer installation time, but more efficient operation and less maintenance over time
- Shatter-resistant and mercury-free, no special disposal is required
- Flicker-free, instant ON illumination at full brightness



Specifications

Item Number	Item Length (In)	Item Width (In)	Bulb Shape
T96/850/B/LEDG2/2	93.9	1.1	T8
Bulb Type	Bulb Base	Tube Type	Brightness (LUMENS)
Tubular	FA8	Type B	5000
Lumen Efficiency (LPW)	Color Accuracy (CRI)	Color Temperature (CCT)	Life Hours
125.0	80	5000	35000
Life Years	Voltage	Replacement	Annual Energy Cost
32.0	120-277	59	4.82
Energy Used (Wattage)	Battery Operated	Pack Quantity	Smart
40	No	2	No
Portable	Dimmable	Hardwire	Enclosed Fixture Rated
No	No	No	Yes
Safety Location	Energy Star	CEC Compliant	
Damp	No	Not Regulated	